

QuickTap IFB™

Telephone Handset IFB Tap



FEATURES

- » Works with Analog, Digital, PBX, and ISDN Telephones
- » 1/8" (3.5mm) Mono Audio Output with Attenuator
- » 600 ohm XLR Output
- » Passive Design. No Battery or AC Required

SPECIFICATIONS

IFB Earpiece

1/8" (3.5 mm) Mono:	600 ohms 100 mV RMS (-16 dBu nom)
---------------------	--------------------------------------

From Phone

Balanced Male XLR:	600 ohms 100 mV RMS (-16 dBu nom)
--------------------	--------------------------------------

Dimensions

Handset and Telephone:	RJ22
Size:	3.7 x 1.6 x 1.3 inch (9.4 x 4.1 x 3.3 cm)
Weight:	5 oz

Monitor the Phone Line with an XLR Output.

Connect the QuickTap IFB between your telephone and handset for quick access to audio from any telephone system.

Both audio output jacks contain a nice mix of the audio coming from the phone line and the handset audio going into the phone. Any conversation over the handset is sent over both audio output jacks. Or you can leave the handset disconnected and just hear audio from the far end of the call.

The QuickTap IFB does not work with cellular telephones or any telephone with a keypad in the handset.

BLOCK DIAGRAM

