



SMART3000RMXL2U Estimated Runtime

| UPS | External Battery Pack | BP QTY | CONNECTED EQUIPMENT LOAD IN WATTS | | | | | | | | | | | | | |
|-----------------|-----------------------|--------|-----------------------------------|-------|-------|-------|-------|-------|-------|-------|-------|-------|-------|-------|-------|-------|
| | | | 200 | 500 | 800 | 1,000 | 1,200 | 1,400 | 1,600 | 1,800 | 2,000 | 2,200 | 2,400 | 2,600 | 2,800 | 2,880 |
| SMART3000RMXL2U | Included Batteries | n/a | 87 | 32 | 19 | 15 | 12 | 10 | 8.4 | 6.9 | 5.8 | 4.9 | 4.2 | 3.6 | 3.2 | 3.0 |
| SMART3000RMXL2U | BP48V24-2U | 1 | 282 | 107 | 62 | 47 | 38 | 31 | 26 | 22 | 19 | 16 | 14 | 13 | 11 | 11 |
| SMART3000RMXL2U | BP48V27-2US | 1 | 384 | 149 | 87 | 67 | 54 | 44 | 37 | 31 | 27 | 23 | 21 | 18 | 17 | 16 |
| SMART3000RMXL2U | BP48V27-2US | 2 | 692 | 281 | 168 | 130 | 105 | 88 | 73 | 62 | 54 | 47 | 42 | 37 | 34 | 33 |
| SMART3000RMXL2U | BP48V27-2US | 3 | 995 | 416 | 253 | 197 | 160 | 134 | 113 | 96 | 83 | 73 | 65 | 58 | 53 | 51 |
| SMART3000RMXL2U | BP48V27-2US | 4 | 1,293 | 551 | 338 | 266 | 217 | 182 | 154 | 131 | 114 | 101 | 90 | 81 | 73 | 71 |
| SMART3000RMXL2U | BP48V27-2US | 5 | 1,584 | 685 | 425 | 335 | 275 | 232 | 195 | 168 | 146 | 129 | 115 | 104 | 94 | 91 |
| SMART3000RMXL2U | BP48V27-2US | 6 | 1,869 | 818 | 511 | 405 | 333 | 281 | 238 | 205 | 179 | 158 | 141 | 128 | 116 | 112 |
| SMART3000RMXL2U | BP48V27-2US | 7 | 2,147 | 950 | 597 | 474 | 391 | 331 | 281 | 242 | 212 | 188 | 168 | 152 | 138 | 133 |
| SMART3000RMXL2U | BP48V27-2US | 8 | 2,420 | 1,081 | 683 | 544 | 449 | 381 | 324 | 279 | 245 | 217 | 195 | 176 | 161 | 155 |
| SMART3000RMXL2U | BP48V27-2US | 9 | 2,687 | 1,211 | 768 | 613 | 507 | 431 | 367 | 317 | 278 | 247 | 222 | 201 | 183 | 177 |
| SMART3000RMXL2U | BP48V27-2US | 10 | 2,948 | 1,340 | 853 | 682 | 566 | 481 | 410 | 355 | 312 | 277 | 249 | 226 | 206 | 199 |
| SMART3000RMXL2U | BP48V60RT-3U | 1 | 569 | 228 | 135 | 104 | 84 | 70 | 58 | 49 | 43 | 37 | 33 | 30 | 27 | 26 |
| SMART3000RMXL2U | BP48V60RT-3U | 2 | 1,055 | 443 | 270 | 211 | 172 | 144 | 121 | 103 | 89 | 79 | 70 | 63 | 57 | 55 |
| SMART3000RMXL2U | BP48V60RT-3U | 3 | 1,526 | 658 | 407 | 321 | 263 | 222 | 187 | 160 | 140 | 123 | 110 | 99 | 90 | 87 |
| SMART3000RMXL2U | BP48V60RT-3U | 4 | 1,981 | 871 | 545 | 432 | 356 | 301 | 255 | 219 | 192 | 170 | 152 | 137 | 125 | 120 |
| SMART3000RMXL2U | BP48V60RT-3U | 5 | 2,420 | 1,081 | 683 | 544 | 449 | 381 | 324 | 279 | 245 | 217 | 195 | 176 | 161 | 155 |
| SMART3000RMXL2U | BP48V60RT-3U | 6 | 2,844 | 1,289 | 819 | 654 | 542 | 461 | 393 | 340 | 298 | 265 | 238 | 216 | 197 | 190 |
| SMART3000RMXL2U | BP48V60RT-3U | 7 | 3,254 | 1,493 | 955 | 765 | 635 | 541 | 462 | 401 | 352 | 314 | 282 | 256 | 234 | 226 |
| SMART3000RMXL2U | BP48V60RT-3U | 8 | 3,650 | 1,694 | 1,089 | 874 | 728 | 621 | 531 | 461 | 406 | 362 | 326 | 296 | 271 | 262 |
| SMART3000RMXL2U | BP48V60RT-3U | 9 | 4,033 | 1,892 | 1,222 | 983 | 820 | 701 | 601 | 522 | 460 | 411 | 371 | 337 | 308 | 298 |
| SMART3000RMXL2U | BP48V60RT-3U | 10 | 4,403 | 2,088 | 1,353 | 1,091 | 911 | 781 | 669 | 583 | 514 | 460 | 415 | 377 | 346 | 334 |

All runtime values are shown in minutes.