

MODEL: PF-228

- Reduces "P" & "T" consonants noises, breath noise and helps prevents excess spittle from contacting the microphone
- Special multi-layer design for maximum effectiveness with all type of speech patterns and voice dynamics
- 3.25" diameter pop filter is ideal size for use on popular broadcast microphones
- Easy to use adjustable clamp with foam and no-slip rubber grips



## FEATURES and SPECIFICATIONS

Spring Steel Fastener

2" Aluminum Self-Adjusting Clamp with foam and rubber sleeve

3.25" Multi-Layer Pop Filter

Aluminum Thread Lock

4.5" Aluminum Extension Rod

Hinge

Pop Filter can be swivel for use at any angle

All metal parts have a black anodized finish that resist corrosion while reduces wear and tear

[www.AmericanRecorder.com](http://www.AmericanRecorder.com)